Emergency Stops, Light Curtains, and Interlocks: Testing Your Safety Systems Regularly

In aluminum and steel bending environments, safety systems act as the final layer of protection. These components are critical; they must work properly at the exact moment they're needed. Regular testing of emergency stops, light curtains, and interlocks helps protect operators and prevents equipment damage. This article explains how to check each system, how often to test, and why staying consistent matters.

Why Regular Safety Testing Matters

To understand the importance of regular safety checks, it helps to look at what can go wrong when systems fail.

Preventing Injuries

When an emergency stop or light curtain doesn't trigger, operators are exposed to moving parts that can cause serious harm. Testing these systems helps catch faults early.

Meeting Legal Requirements

OSHA regulations and EU Machinery Directive rules require safety systems to function correctly. Testing shows that your shop is meeting these legal standards and avoiding penalties.

For reference, OSHA standard 1910.212 (general requirements for machine guarding) and EU Machinery Directive 2006/42/EC, Annex I (Essential Health and Safety Requirements), both require protective devices such as emergency stops and guards to be maintained and tested regularly.

Lowering Liability Risks

Regular safety checks create a record that proves you took the right steps to protect your team and follow safety procedures.

Protecting Equipment

Safety stops and interlocks help avoid crashes and prevent movement beyond limits. This keeps machines in good condition and reduces costly downtime.

System Overview and Testing Frequency

Each safety system handles a specific task. Keeping track of their role and knowing how often to test helps avoid errors and keeps everything running safely.

Safety System	What It Does	How Often to Test
Emergency Stops (E-Stops)	Stops all machine movement right away*	Every shift, or daily

Light Curtains	Detects when someone enters a danger zone	Daily, or before each batch
Interlock Gates	Prevents the machine from running with a guard open	Weekly, or after maintenance

Some equipment manufacturers recommend even more frequent testing. This is especially true after software updates or electrical work. Always follow your machine manual.

While daily or weekly tests are common, the actual test interval should be based on a formal risk assessment, as outlined in ISO 12100 and ISO 13849.

**Some E-stops may only halt motion but not cut all power, depending on the machine's safety category. Always verify the intended behavior according to the manufacturer's documentation*.

How to Test Each System



When it comes to testing, each system needs its own approach. These simple steps will help confirm everything is working the way it should.

Emergency Stops

Run the machine as normal, then press the E-stop.

- The machine should stop right away.
- It must remain off until you manually reset the button.
- After resetting, it should only move again if you press the start button.

Light Curtains

Turn the machine on and have it ready (but not running). Then interrupt the light beam using a rod or another object.

- The machine should stop immediately.
- It should stay in a locked-out state until reset.

    - Depending on the safety circuit design, breaking the beam may stop the machine without fully locking it out. For high-risk applications, systems should meet Category 4 performance with redundant safety relays.
- Check for any alerts or lockout messages on the display.

Interlock Gates

With the machine powered on but idle, open a guard or access panel.

- Machine movement must stop or stay disabled while the gate is open.
    - Some gates use monitored or coded interlocks that delay shutdown or track tampering. Always check if your system uses a mechanical switch, solenoid-locking device, or RFID safety sensor.
- The display should show a warning or lockout signal.
- Some machines may also trigger an audible alert.

Common Issues and Fixes

When a system doesn't pass a test, repairs should come first—before production resumes. Here are typical issues and what usually causes them:

Problem	Cause	How to Fix It
Loose wiring or bad relays	Vibration or wear over time	Secure connections and replace faulty components
Safety logic left bypassed	A leftover override from maintenance	Remove the bypass and secure the control panel
Sensors covered with dirt or grease	Coolant or debris buildup	Clean sensors and use covers where needed
Wrong reset procedures	Operators skipping proper steps	Update settings to require a two-step restart or supervisor input

Documentation and Recordkeeping

Testing helps only if you can prove it was done. That's where documentation comes in. Use a Safety System Inspection Checklist and record the following:

- Date and time of the test
- Pass or fail result
- Technician's name or initials

Hold onto these records for at least 12 months, or longer if your company policy requires it. If a system fails, take the machine offline until the issue is fixed.

Conclusion

Safety systems that don't get tested are safety systems you can't rely on. A single fault in an emergency stop, a light curtain, or an interlock can lead to injury, damage, or costly downtime. Checking these components regularly keeps your workplace safer and your machines in better condition.

Good safety isn't about one big decision. It comes from steady habits. Testing your safety systems on a regular schedule helps you catch small problems before they grow into major failures. Clear procedures, proper records, and fast action when something fails are what keep your team and equipment protected. Safety is part of the job, and it starts with the checks you do every day.

Follow Inductaflex for more information.